

# **YOUR VOICE MAIL SYSTEM**

**AUDIX SYSTEM #: 6556**

## **RECORD MESSAGE**

- 1.** Press 1.
- 2.**

**PRESS**

**RECORD  
MESSAGES**

PRESS

A B C

2

GET  
MESSAGES

### LISTEN TO MESSAGE

1. Press 2.
2. Listen to message header
3. Press 0 and listen to message.

#### Options -

- \* Respond go to step 4.
- \* Press **2 3** to play back summary.
- \* Press \* **D** to delete and skip to next summary. If, immediately after deleting a message, you need to restore it, press \* \* **U** to undelete the message.
- \* Press # to save and skip to next summary.

### RESPOND TO MESSAGE

4. Choose one:
  - \* Call sender directly, press **1 0**.
  - \* *Reply by voice mail:*

-- Press **1 7** and speak message (to send reply only)

OR

Press **1 1 9** and speak message (to attach original).

-- Press \* \* # to approve and send NOW.

OR

Press \* # to approve and send with options.

- \* Forward with comment, press **1 2**. Go to **RECORD MESSAGES** step 2 above.

### ACTIVITY MENU

**Record and Send Messages** (record, edit, address, deliver)

1

**Get and Respond to Messages** (retrieve, sort/save, respond)

ABC  
2

**Create Personal Greetings** (record, edit, activate)

DEF  
3

**Check Outgoing Messages** (retrieve, sort/save/ review/ modify, resend)

GHI  
4

**Change Password/ Create Lists/ Personal Directories** (create, review/modify, scan)

JKL  
5

**Scan Messages Quickly** (and/or headers)

PRS  
7

**RECORD  
GREETING**

1. Press **3**.
2. Listen to greeting number in use.
3. Press **1** to create/change greeting.
4. Indicate greeting number you will record (1-9)
5. Speak greeting.

**Edit –**  
! Press **1** to stop/pause.  
Then  
Press **1** to continue.  
! Press **2 3** to play back  
! Press **\* D** to delete and re-record.  
(Begin at step 5.)

6. When finished, press **\* #** to approve.

**USE GREETING**

7. Press **1** to use greeting for all calls.

**OR**

Press **\* #**

**PRESS**

**ADMINISTER  
GREETINGS**

**PRESS**

**J K L**

**5**

**CHANGE  
PASSWORD/  
ADMINISTER LISTS**

### CHANGE PASSWORD

1. Press **5 4**.
2. Enter new password (up to 15 digits, 0-9) and press #.
3. Re-enter new password and press #.

### TIPS

- ! To alternate between extension and name addressing, press **\*A**.
- ! When addressing a message, press **\*M** and  
1 to make message private,  
2 to make message priority, then **\*#** to continue addressing.
- ! To approve and send a message NOW, press **\*\*#**.
- ! To bypass greetings, press **1** as soon as the system answers and speak your message.

### PLAY-BACK CONTROLS

**Rewind    Play/Pause**

1	ABC 2	DEF 3
---	----------	----------

**Louder    Back Up    Advance**

GHI 4	JKL 5	MNO 6
----------	----------	----------

**Softer    Slower    Faster**

PRS 7	TUV 8	WXY 9
----------	----------	----------

**Listen/Replay    Skip**

*	Oper 0	#
---	-----------	---

**Press 3 to pause and 3 again to continue. Q=7 Z=9**

**Voice messaging wallet card  
585-300-704, Issue 2, 11/93**

### FOR MORE INFORMATION

- ! Press **\*H** for HELP.
- ! See reverse side for complete voice mail system flow chart.
- ! Contact your system administrator at **3535**

## LOG IN

- Dial your voice messaging system number.  
(You may need to dial an extension only, a complete local phone number, or, for long distance, the area code and phone number.)
- Enter extension # (if calling from your extension, enter #)
- Enter password #.
- Get your initial password from your system administrator.

## ACTIVITY MENU

1	Record and Send Messages
ABC 2	Get and Respond to Messages
DEF 3	Create Personal Greetings
GHI 4	Check Outgoing Messages
JKL 5	Change Password/Create Lists/Personal Directories
PRS 7	Scan Messages Quickly

## BASIC COMMANDS

\*Use while addressing: L or 5

- Help
- Return to Activity Menu
- Delete
- Undelete (may not be available with your system)
- Wait
- Transfer out of system
- Look up name/ ext. in Directory
- Exit system
- Hold message in category
- Use while addressing:**
- Alternate addressing (switch between name/ ext.)
- Use mailing list

### More Extensions or Names

Extension or Name #  
(press \*A or \*2 to alternate between Ext. and Name) and/or  
Group List \*L or \*5

Finish Addressing #

Reply by Voice Mail:  
-without copy  
-with copy  
Forward with Comment  
New Message  
Call Sender  
Return to previous menu

Record Message

Stop Recording/Restart 1  
Play Back 23  
Delete \*D or \*3  
Approve #

Hear Message Summary

Listen 0  
Replay Header 23

Hear Greeting Number(s) in Use

Listen 0  
Change/Create/Delete 1  
Scan 2  
Activate 3  
Call Type 4  
Finished? #

Hear Message Summary

Listen 0  
Change/Resend 1  
Replay Header 23  
Delete \*D or \*3  
Skip #  
Next Category \*\*

\*Use while addressing:

Mailing Lists 1  
Personal Directory 2  
Password 4  
Re-record name 5

Scan Headers and Messages 1  
Scan Headers 2  
Scan Messages 3

## PLAY-BACK CONTROLS

**Note:** AUDIX R1V8 Standard and DEFINITY AUDIX R3.0 offer the \*\*U (or \*\*8) command to recover a message you just deleted and the # command to back out of the Reply to Sender option. However, these commands may not be available on all voice messaging systems AT&T offers subsequent to these products.